

Error-Trellis State Complexity of LDPC Convolutional Codes Based on Circulant Matrices

Masato Tajima

Dept of Intellect. Inform. Systems Eng.
University of Toyama
Toyama 930-8555, Japan
tajima@eng.u-toyama.ac.jp

Koji Okino

Information Technology Center
University of Toyama
Toyama 930-8555, Japan
okino@itc.u-toyama.ac.jp

Takashi Miyagoshi

Dept of Intellect. Inform. Systems Eng.
University of Toyama
Toyama 930-8555, Japan
miyagosi@eng.u-toyama.ac.jp

Abstract—Let $H(D)$ be the parity-check matrix of an LDPC convolutional code corresponding to the parity-check matrix H of a QC code obtained using the method of Tanner et al. We see that the entries in $H(D)$ are all monomials and several rows (columns) have monomial factors. Let us cyclically shift the rows of H . Then the parity-check matrix $H'(D)$ corresponding to the modified matrix H' defines another convolutional code. However, its free distance is lower-bounded by the minimum distance of the original QC code. Also, each row (column) of $H'(D)$ has a factor different from the one in $H(D)$. We show that the state-space complexity of the error-trellis associated with $H'(D)$ can be significantly reduced by controlling the row shifts applied to H with the error-correction capability being preserved.

I. INTRODUCTION

In this paper, we assume that the underlying field is $F = \text{GF}(2)$. Let $G(D)$ be a polynomial generator matrix for an (n_0, k_0, ν) convolutional code C with memory ν . Denote by $H(D)$ a corresponding parity-check matrix. Both $G(D)$ and $H(D)$ are assumed to be canonical [4], [5]. In this case, the code-trellis module associated with $G(D)$ and the error-trellis modules [6] associated with the syndrome former $H^T(D)$ (T means transpose) have 2^ν states, where the obvious realization of $G(D)$ and the adjoint-obvious realization [3] of $H^T(D)$ are assumed, respectively. Ariel and Snyders [1] presented a construction of an error-trellis based on the scalar check matrix derived from $H(D)$. They showed that when some (j th) “column” of $H(D)$ has a factor D^l (i.e., the j th column is not “delay free”), there is a possibility that state-space reduction can be realized. Being motivated by their work, we also examined the same case. We took notice of a syndrome generation process. The time- k error e_k and the time- k syndrome ζ_k are connected with the relation $\zeta_k = e_k H^T(D)$. From this relation, we noticed [8] that the transformation $e_k^{(j)} \rightarrow D^l e_k^{(j)} = e_{k-l}^{(j)}$ is equivalent to dividing the j th column of $H(D)$ by D^l . That is, reduction can be accomplished by shifting the “subsequence” $\{e_k^{(j)}\}$ of the original error-path.

On the other hand, consider the parity-check matrix

$$H_1(D) \triangleq \begin{pmatrix} D^2 & D^2 & 1 \\ 1 & 1 + D + D^2 & 0 \end{pmatrix}. \quad (1)$$

Since $H_1(D)$ is canonical and all the columns are delay free, any further reduction seems to be impossible. In fact, it follows from *Theorem 1* of [1] that the dimension d_1 of the state

space of the error-trellis based on $H_1^T(D)$ is 4. However, a corresponding generator matrix is given by $G_1(D) \triangleq (1 + D + D^2, 1, D^3 + D^4)$. Note that the third column of $G_1(D)$ has a factor D^2 . (*Remark:* It suffices to divide the third column by D^2 in order to obtain a reduced code-trellis.) This fact implies that a reduced error-trellis can be constructed [1], [8] (i.e., state-space reduction can be realized). Then consider the reciprocal dual encoder [4]

$$\tilde{H}_1(D) \triangleq \begin{pmatrix} 1 & 1 & D^2 \\ D^2 & 1 + D + D^2 & 0 \end{pmatrix}. \quad (2)$$

Note that the third column of $\tilde{H}_1(D)$ has a factor D^2 . Accordingly, dividing the third column of $\tilde{H}_1(D)$ by D^2 , we can construct an error-trellis with 4 states (i.e., $\tilde{d}_1 = 2$) [1], [8]. Here, notice that each error-path in the error-trellis based on $H_1^T(D)$ can be represented in time-reversed order using the error-trellis based on $\tilde{H}_1^T(D)$. Hence, a factor D^2 in the column of $\tilde{H}_1(D)$ corresponds to backward-shifting by two time units (i.e., D^{-2}) in terms of the original $H_1(D)$. Actually, by “multiplying” the third column of $H_1(D)$ by D^2 , we have

$$H'_1(D) \triangleq \begin{pmatrix} D^2 & D^2 & D^2 \\ 1 & 1 + D + D^2 & 0 \end{pmatrix}. \quad (3)$$

Note that this matrix can be reduced to an equivalent canonical parity-check matrix

$$H''_1(D) \triangleq \begin{pmatrix} 1 & 1 & 1 \\ 1 & 1 + D + D^2 & 0 \end{pmatrix} \quad (4)$$

by dividing the first “row” by D^2 . Hence, the dimension d_1 can be reduced to 2. (*Remark:* This fact cannot be derived from the results of [1].) It follows from the above argument that there is a possibility that a reduced error-trellis can be constructed not only using forward-shifted error subsequences but also using backward-shifted error subsequences.

Now, we remark that a parity-check matrix $H(D)$ with the form described above appears in [10]. Tanner et al. [10] presented a class of algebraically constructed quasi-cyclic (QC) LDPC codes and their convolutional counterparts. It is stated that the convolutional codes obtained in the paper typically have large constraint lengths and therefore the use of trellis-based decoding is not feasible. However, the parity-check matrices of LDPC convolutional codes proposed by

Tanner et al. have monomial entries. Accordingly, the above-mentioned state-space reduction method can be directly applied to those parity-check matrices. Then we intended to evaluate the state-space complexity of the error-trellis of an LDPC convolutional code which appears in [10]. We show that the *overall constraint length* (abbreviated as “OCL” in this paper) of the parity-check matrix which specifies an LDPC convolutional code can be significantly reduced with the error-correction capability of the convolutional code being preserved.

II. PRELIMINARIES

A. Error-Trellis Construction Using Shifted Error/Syndrome Subsequences

Let $H(D)$ be a parity-check matrix for an (n_0, k_0) convolutional code C . In this paper, we consider the error-trellis based on the syndrome former $H^T(D)$. In this case, the adjoint-obvious realization of $H^T(D)$ is assumed unless otherwise specified. Denote by $e_k = (e_k^{(1)}, \dots, e_k^{(j)}, \dots, e_k^{(n_0)})$ and $\zeta_k = (\zeta_k^{(1)}, \dots, \zeta_k^{(i)}, \dots, \zeta_k^{(r)})$ the time- k error and the time- k syndrome, respectively, where $r = n_0 - k_0$. Then we have the relation:

$$\zeta_k = e_k H^T(D). \quad (5)$$

Assume that the i th row of $H(D)$ has the form

$$(D^{l_i} h'_{i1}(D) \quad D^{l_i} h'_{i2}(D) \quad \dots \quad D^{l_i} h'_{i n_0}(D)), \quad (6)$$

where $l_i \geq 1$. Let $H'(D)$ be the modified version of $H(D)$ with the i th row being replaced by

$$(h'_{i1}(D) \quad h'_{i2}(D) \quad \dots \quad h'_{i n_0}(D)). \quad (7)$$

Defining ζ'_k as $\zeta'_k \triangleq D^{l_i} \zeta_k^{(i)} = \zeta_{k-l_i}^{(i)}$, we set $\zeta'_k \triangleq (\zeta_k^{(1)}, \dots, \zeta_k^{(i)}, \dots, \zeta_k^{(r)})$. Then we have

$$\zeta'_k = e_k H'^T(D). \quad (8)$$

Similarly, assume that the j th column of $H(D)$ has the form

$$(D^{l_j} h'_{1j}(D) \quad D^{l_j} h'_{2j}(D) \quad \dots \quad D^{l_j} h'_{rj}(D))^T, \quad (9)$$

where $l_j \geq 1$. (Remark: $H(D)$ is not basic [2] and then not canonical.) Let $H'(D)$ be the modified version of $H(D)$ with the j th column being replaced by

$$(h'_{1j}(D) \quad h'_{2j}(D) \quad \dots \quad h'_{rj}(D))^T. \quad (10)$$

Also, let $e'_k \triangleq (e_k^{(1)}, \dots, e_k^{(j)}, \dots, e_k^{(n_0)})$, where $e_k^{(j)} \triangleq D^{l_j} e_k^{(j)} = e_{k-l_j}^{(j)}$. Then we have

$$\zeta_k = e'_k H'^T(D). \quad (11)$$

Noting these relations [8], [9], in the case where the i th row of $H(D)$ has a factor D^{l_i} , by shifting the i th syndrome subsequence by l_i time units, whereas in the case where the j th column of $H(D)$ has a factor D^{l_j} , by shifting the j th error subsequence by l_j time units, we can construct an error trellis with reduced number of states. In the following, we call factoring out D^l from a row of $H(D)$ and from a column of $H(D)$ “row operation” and “column operation”, respectively.




Fig. 1. Example error-trellis based on $H_2^T(D)$.

B. Error-Trellis Construction Based on a Reciprocal Dual Encoder

Consider the $(3, 1, 2)$ convolutional code C_2 with canonical parity-check matrix given by

$$H_2(D) \triangleq \begin{pmatrix} D & 0 & 1 \\ 1 & 1+D & 0 \end{pmatrix}. \quad (12)$$

In this subsection, we discuss using this specific example. However, the argument is entirely general. Since the columns of $H_2(D)$ are delay free, the dimension d_2 of the state space of the error-trellis based on the syndrome former $H_2^T(D)$ is given by 2 (see Theorem 1 of [1]). Fig.1 shows an error-trellis constructed based on $H_2^T(D)$ using the conventional method [6]. It is assumed that a transmitted code-path is terminated in the all-zero state at $t = 4$ and the corresponding received data is given by $z = z_1 \ z_2 \ z_3 \ z_4 \ z_5 = 010 \ 011 \ 000 \ 001 \ 000$, where $z_5 = 000$ is the imaginary received data. Let z be the input of the syndrome former $H_2^T(D)$, then we have the syndrome sequence $\zeta = \zeta_1 \ \zeta_2 \ \zeta_3 \ \zeta_4 \ \zeta_5 = 01 \ 10 \ 01 \ 10 \ 00$. The overall error-trellis is constructed by concatenating five error-trellis modules corresponding to ζ_k . Note that the error-trellis in Fig.1 is terminated in state (00) at $t = 5$, which corresponds to the final syndrome-former state $\sigma_5 = (00)$. From Fig.1 (note that $e_5 = 000$), we have four admissible error-paths:

$$e_{p_1} = 010 \ 011 \ 000 \ 001 \ 000 \quad (13)$$

$$e_{p_2} = 010 \ 101 \ 101 \ 000 \ 000 \quad (14)$$

$$e_{p_3} = 100 \ 000 \ 100 \ 000 \ 000 \quad (15)$$

$$e_{p_4} = 100 \ 110 \ 001 \ 001 \ 000. \quad (16)$$

Next, consider the reciprocal dual encoder

$$\tilde{H}_2(D) \triangleq \begin{pmatrix} 1 & 0 & D \\ D & 1+D & 0 \end{pmatrix}. \quad (17)$$

Let $\tilde{z} = z_4 \ z_3 \ z_2 \ z_1 \ z_0 = 001 \ 000 \ 011 \ 010 \ 000$ be the time-reversed received data of $\{z_k\}_{k=1}^4$ augmented with the imaginary data $z_0 = 000$. If $\tilde{z}$ is inputted to the syndrome former $\tilde{H}_2^T(D)$, then the time-reversed syndrome sequence $\tilde{\zeta} = \zeta_5 \ \zeta_4 \ \zeta_3 \ \zeta_2 \ \zeta_1 = 00 \ 10 \ 01 \ 10 \ 01$ is obtained. The




Fig. 2. Error-trellis based on $\tilde{H}_2^T(D)$.

corresponding error-trellis is shown in Fig.2, where the trellis is terminated in state (00), which corresponds to the final syndrome-former state $\tilde{\sigma}_5 = (00)$. From Fig.2, we have four admissible error-paths:

$$\tilde{e}_{q_1} = 001\ 000\ 011\ 010\ 000 \quad (18)$$

$$\tilde{e}_{q_2} = 000\ 101\ 101\ 010\ 000 \quad (19)$$

$$\tilde{e}_{q_3} = 000\ 100\ 000\ 100\ 000 \quad (20)$$

$$\tilde{e}_{q_4} = 001\ 001\ 110\ 100\ 000. \quad (21)$$

Compare these error-paths with those in Fig.1. We observe that each error-path in Fig.2 (restricted to the section $[0, 4]$) is represented in Fig.1 in time-reversed order. That is, the original error-paths can be represented using the error-trellis associated with the corresponding reciprocal dual encoder.

On the other hand, dividing the third column of $\tilde{H}_2(D)$ by D , we have the reduced canonical parity-check matrix

$$\tilde{H}'_2(D) \triangleq \begin{pmatrix} 1 & 0 & 1 \\ D & 1+D & 0 \end{pmatrix}. \quad (22)$$

In this case [1], [8], error-paths associated with $\tilde{H}'_2(D)$ can be represented using the error-trellis constructed based on $\tilde{H}'_2{}^T(D)$. Note that a factor D^l in the column of $\tilde{H}(D)$ corresponds to backward-shifting by l time units (i.e., D^{-l}) in terms of the original $H(D)$. This observation implies that error-trellis state-space reduction can be equally accomplished using backward-shifted error subsequences.

III. QC CODES AND CORRESPONDING LDPC CONVOLUTIONAL CODES

A. LDPC Convolutional Codes Based on Circulant Matrices

Each circulant in the parity-check matrix of a QC block code can be specified by a unique polynomial; the polynomial represents the entries in the first column of the circulant matrix. For example, a circulant matrix whose first column is $[1\ 1\ 1\ 0\ 1\ 0]^T$ is represented by the polynomial $1 + D + D^2 + D^4$. Using this correspondence, an LDPC convolutional code is constructed based on a parity-check matrix H of a given QC code [10].

For example [10], let

$$H = \begin{pmatrix} I_1 & I_2 & I_4 & I_8 & I_{16} \\ I_5 & I_{10} & I_{20} & I_9 & I_{18} \\ I_{25} & I_{19} & I_7 & I_{14} & I_{28} \end{pmatrix} \quad (23)$$

be the parity-check matrix of a $(155, 64)$ QC code ($m = 31$), where I_x is a 31×31 identity matrix with rows shifted cyclically to the left by x positions. From H we obtain the following parity-check matrix with polynomial entries:

$$H(D) = \begin{pmatrix} D & D^2 & D^4 & D^8 & D^{16} \\ D^5 & D^{10} & D^{20} & D^9 & D^{18} \\ D^{25} & D^{19} & D^7 & D^{14} & D^{28} \end{pmatrix}. \quad (24)$$

(Remark: It is stated [10] that the LDPC convolutional code is obtained by *unwrapping the constraint graph* (i.e., Tanner graph) of the QC code.) Note that the polynomials in $H(D)$ are all monomials. In this paper, we discuss exclusively using this specific example. However, the argument is entirely general.

B. Reordering Rows of H and the Corresponding $H(D)$

Again, consider the parity-check matrix H of the $(155, 64)$ QC code. Let us cyclically shift the first block of $m = 31$ rows above by one position, the middle block of 31 rows by five positions, and the last block of 31 rows by 25 positions. The resulting matrix is given by

$$H' = \begin{pmatrix} I_0 & I_1 & I_3 & I_7 & I_{15} \\ I_0 & I_5 & I_{15} & I_4 & I_{13} \\ I_0 & I_{25} & I_{13} & I_{20} & I_3 \end{pmatrix}. \quad (25)$$

Clearly, the QC block code and its associated constraint graph are unaffected by these row shifts. However, the convolutional code obtained based on the above procedure has the parity-check matrix

$$H'(D) = \begin{pmatrix} 1 & D & D^3 & D^7 & D^{15} \\ 1 & D^5 & D^{15} & D^4 & D^{13} \\ 1 & D^{25} & D^{13} & D^{20} & D^3 \end{pmatrix}. \quad (26)$$

We see that $H'(D)$ is not equivalent to $H(D)$. Two convolutional codes specified by $H(D)$ and $H'(D)$ are in fact different. We also remark that $H(D)$ and $H'(D)$ have different monomial entries and accordingly, when row/column factors are factored out, the resulting matrices have different OCLs.

On the other hand, we have the following important fact [10]:

Property: The LDPC convolutional codes obtained by unwrapping the constraint graph of the QC codes have their free distance d_{free} lower-bounded by the minimum distance d_{min} of the corresponding QC code.

It is shown that the QC code associated with H has a minimum distance $d_{min} = 20$. Then d_{free} of the convolutional code C specified by $H(D)$ is lower-bounded by $d_{min} = 20$. (It is conjectured that C has a free distance d_{free} of 24 [10].) From the above property, we also have $d'_{free} \geq d_{min} = 20$, where d'_{free} is the free distance of the convolutional code C' specified by $H'(D)$. In general, let $H'(D)$ be the parity-check matrix associated with H' , where H' is the parity-check matrix

obtained by applying cyclic shifts to the rows of each block of the original H . Above observations imply that the OCL of $H'(D)$ can be controlled to some extent with its free distance d'_{free} being lower-bounded by the minimum distance d_{min} of the QC code specified by H .

IV. REDUCTION OF OVERALL CONSTRAINT LENGTH

A. Row/Column Operations and Their Equivalent Representation

Again, take the parity-check matrix H given by Eq.(23). Here, let us cyclically shift the first block of 31 rows above by one position. Then the first block $[I_1 I_2 I_4 I_8 I_{16}]$ changes to $[I_0 I_1 I_3 I_7 I_{15}]$. That is, the subscript number of each entry decreases by 1. According to this change in H , the first row of $H(D)$ changes from $[D D^2 D^4 D^8 D^{16}]$ to $[1 D D^3 D^7 D^{15}]$. In terms of the power of D , this change is expressed as $[1 2 4 8 16] \rightarrow [0 1 3 7 15]$. In general, we observe that each entry decreases by one (modulo 31) when we cyclically shift the rows above by one position. Continuing this procedure (*Remark: it is assumed that row operations have been done*), we see that the first row of $H(D)$ corresponds to one of the following five patterns in terms of the power of D :

$$\begin{cases} P_1 = [0 1 3 7 15] \\ P_2 = [30 0 2 6 14] \\ P_3 = [28 29 0 4 12] \\ P_4 = [24 25 27 0 8] \\ P_5 = [16 17 19 23 0] \end{cases} \quad (27)$$

Similarly, the second and third rows of $H(D)$ are represented by

$$\begin{cases} Q_1 = [0 5 15 4 13] \\ Q_2 = [26 0 10 30 8] \\ Q_3 = [16 21 0 20 29] \\ Q_4 = [27 1 11 0 9] \\ Q_5 = [18 23 2 22 0] \end{cases} \quad \text{and} \quad \begin{cases} R_1 = [0 25 13 20 3] \\ R_2 = [6 0 19 26 9] \\ R_3 = [18 12 0 7 21] \\ R_4 = [11 5 24 0 14] \\ R_5 = [28 22 10 17 0] \end{cases}, \quad (28)$$

respectively. Hence, when we apply cyclic shifts to the rows of each block of the original H , the resulting $H(D)$ can be specified by a pattern $[P_i, Q_j, R_k]^T$. For example, consider the pattern $[P_1, Q_1, R_3]^T$. The corresponding $H(D)$ (cf. Eq.(24)) is given by

$$H(D) = \begin{pmatrix} 1 & D & D^3 & D^7 & D^{15} \\ 1 & D^5 & D^{15} & D^4 & D^{13} \\ D^{18} & D^{12} & 1 & D^7 & D^{21} \end{pmatrix}. \quad (29)$$

Since row operations have been done, let us apply column operations. Then we have

$$H'(D) = \begin{pmatrix} 1 & 1 & D^3 & D^3 & D^2 \\ 1 & D^4 & D^{15} & 1 & 1 \\ D^{18} & D^{11} & 1 & D^3 & D^8 \end{pmatrix}. \quad (30)$$

We see that this is equivalent to the transformation from

$$S = \begin{pmatrix} 0 & 1 & 3 & 7 & 15 \\ 0 & 5 & 15 & 4 & 13 \\ 18 & 12 & 0 & 7 & 21 \end{pmatrix} \quad (31)$$




Fig. 3. Overall constraint length of a reduced $H'(D)$.




Fig. 4. Overall constraint length of a reduced $\tilde{H}'(D)$.

to

$$S' = \begin{pmatrix} 0 & 0 & 3 & 3 & 2 \\ 0 & 4 & 15 & 0 & 0 \\ 18 & 11 & 0 & 3 & 8 \end{pmatrix}, \quad (32)$$

where subtraction is performed in each column of S in order that the minimum is equal to zero. From S' , the OCL of the reduced $H'(D)$ is obtained as $3 + 15 + 18 = 36$.

B. Reduction of Overall Constraint Length: Search Results

As we have seen in the previous section, there are $5 \times 5 \times 5 = 125$ patterns in total. By applying column operations to each pattern, we examined the OCL μ of the corresponding reduced parity-check matrix $H'(D)$. The result is shown in Fig.3, where the horizontal axis represents the OCL μ and the vertical axis represents its frequency. Observe that the minimum OCL μ_{min} is 35, whereas the maximum OCL μ_{max} is 83. That is, the values of μ cover a wide range. Next, based on the argument in Section II-B, we examined the OCL η using the reciprocal dual encoder $\tilde{H}(D)$ associated with $H(D)$. The result is shown in Fig.4. We have $\eta_{min} = 31$ and $\eta_{max} = 85$. Note that in this example, the minimum OCL is further reduced using a reciprocal dual encoder. Moreover, after having applied row/column operations to each $H(D)$ (denote by $H'(D)$ the resulting matrix), we took its reciprocal version $\tilde{H}'(D)$. Then again applying row/column operations to $\tilde{H}'(D)$, we examined the OCL μ' of the resulting matrix. Using this method, we have further reduction with respect to




Fig. 5. Additional overall-constraint-length reduction.

the value of μ . The result is shown in Fig.5. We observe that the maximum reduction $\Delta\mu (= \mu - \mu' \geq 0)$ of 16 is realized. We remark that $\mu_{min} = 35$ is reduced to $\mu' = 34$ using this method.

C. Efficient Search Method

Our aim is the reduction of the OCL of a parity-check matrix $H(D)$. Since row operations have been done in a pattern $[P_i, Q_j, R_k]^T$, it is desirable for figures in each column to be close together (i.e., the difference δ_j between the maximum and the minimum in the j th column is small). In this case, each figure in the column becomes small after the column operation, which finally leads to the reduction of the OCL. Hence, we search for a pattern in which every column has $\delta_j \leq \Delta$, where Δ is a predetermined search parameter.

For example, set $\Delta = 20$. Consider the pattern $[P_2, Q_4, R_3]^T$:

$$S_1 = \begin{pmatrix} 30 & 0 & 2 & 6 & 14 \\ 27 & 1 & 11 & 0 & 9 \\ 18 & 12 & 0 & 7 & 21 \end{pmatrix}. \quad (33)$$

δ_j are given by 12, 12, 11, 7, and 12, respectively and remain within $\Delta = 20$. Applying column operations, we have

$$S'_1 = \begin{pmatrix} 12 & 0 & 2 & 6 & 5 \\ 9 & 1 & 11 & 0 & 0 \\ 0 & 12 & 0 & 7 & 12 \end{pmatrix}. \quad (34)$$

The OCL is given by $12 + 11 + 12 = 35$.

Similarly, consider the pattern $[P_5, Q_5, R_5]^T$:

$$S_2 = \begin{pmatrix} 16 & 17 & 19 & 23 & 0 \\ 18 & 23 & 2 & 22 & 0 \\ 28 & 22 & 10 & 17 & 0 \end{pmatrix}. \quad (35)$$

In this case, δ_j are given by 12, 6, 17, 6, and 0, respectively. Applying column operations, we have

$$S'_2 = \begin{pmatrix} 0 & 0 & 17 & 6 & 0 \\ 2 & 6 & 0 & 5 & 0 \\ 12 & 5 & 8 & 0 & 0 \end{pmatrix}. \quad (36)$$

Again, the OCL is given by $17 + 6 + 12 = 35$. Observe that these patterns have $\mu_{min} = 35$.

V. CONCLUSION

In this paper, we examined the state-space complexity of the error-trellis of an LDPC convolutional code derived from the QC block code specified by a parity-check matrix H . Since the entries in the corresponding parity-check matrix $H(D)$ are all monomials, we can construct a reduced error-trellis using the method of [1] or that of [8]. We noticed that when cyclic shifts are applied to the rows of H , the QC code remains unchanged, whereas the corresponding parity-check matrix $H'(D)$, which defines another convolutional code, has row/column factors different from those in the original $H(D)$. That is, the OCL of $H''(D)$, where $H''(D)$ is the matrix obtained by factoring out row/column factors in $H'(D)$, varies depending on the row shifts applied to H . On the other hand, the free distance of the resulting convolutional code is still lower-bounded by the minimum distance of the original QC code. These facts imply that the state-space complexity of the error-trellis associated with $H'(D)$ can be controlled to some extent with the error-correction capability being preserved and this is our basic idea. By applying our method to the example in [10], we have shown that the OCL of the parity-check matrix of an LDPC convolutional code can be significantly reduced compared to the average one. The LDPC convolutional codes proposed by Tanner et al. have large constraint lengths. Therefore, it is stated [10] that the use of trellis-based decoding is not feasible. We basically agree on this point. However, it has been shown that an error-trellis with much lower state-space complexity than we imagined can be constructed, which gives some prospect of trellis-based decoding.

ACKNOWLEDGMENT

This work was supported in part by the Japan Society for the Promotion of Science, under Grant-in-Aid No. 19500011.

REFERENCES

- [1] M. Ariel and J. Snyders, "Error-trellises for convolutional codes—Part I: Construction," *IEEE Trans. Commun.*, vol. 46, no. 12, pp. 1592–1601, Dec. 1998.
- [2] G. D. Forney, Jr., "Convolutional codes I: Algebraic structure," *IEEE Trans. Inform. Theory*, vol. IT-16, no. 6, pp. 720–738, Nov. 1970.
- [3] ———, "Structural analysis of convolutional codes via dual codes," *IEEE Trans. Inform. Theory*, vol. IT-19, no. 4, pp. 512–518, July 1973.
- [4] R. Johannesson and K. S. Zigangirov, *Fundamentals of Convolutional Coding*. New York: IEEE Press, 1999.
- [5] R. J. McEliece and W. Lin, "The trellis complexity of convolutional codes," *IEEE Trans. Inform. Theory*, vol. 42, no. 6, pp. 1855–1864, Nov. 1996.
- [6] J. P. M. Schalkwijk and A. J. Vinck, "Syndrome decoding of convolutional codes," *IEEE Trans. Commun.*, vol. COM-23, pp. 789–792, July 1975.
- [7] V. Sidorenko and V. Zyablov, "Decoding of convolutional codes using a syndrome trellis," *IEEE Trans. Inform. Theory*, vol. 40, no. 5, pp. 1663–1666, Sept. 1994.
- [8] M. Tajima, K. Okino, and T. Miyagoshi, "Error-trellis construction for convolutional codes using shifted error-subsequences," in *Proc. SITA2005*, pp. 773–776, Nov. 2005 (in Japanese).
- [9] ———, "Error-trellis construction for convolutional codes using shifted syndrome-subsequences," in *Proc. SITA2006*, pp. 295–298, Nov. 2006 (in Japanese).
- [10] R. M. Tanner, D. Sridhara, A. Sridharan, T. E. Fuja, and D. J. Costello, Jr., "LDPC block and convolutional codes based on circulant matrices," *IEEE Trans. Inform. Theory*, vol. 50, no. 12, pp. 2966–2984, Dec. 2004.